Driver installation procedure:

Driver Download link: <u>https://downloads.kyoceradocumentsolutions.com.au/Drivers/KX_Driver.zip</u> (Extract the Zip, open the "en" folder and run the "setup.exe" file)

1. Select Express Install.

🔇 Kyocera 🖡	Product Library	-	×
Prod	uct Library		
<u></u>	Express Install Add single device and its default drivers		
, ↓ °	Custom Install Add multiple devices and printing utilities		
×	Maintenance Run utility programs		
	Uninstall Remove devices, drivers, and utilities		
	© 2021 KYOCERA Document Solutions Inc.		

2. Select the printer to be installed and tick KX Driver before clicking install.

elect the device you	want to add.		Search devices	0
Device		Details		^
TASKalfa 6052ci		fe80::217:c8ff:fe28:6595		ं
TASKalfa 6052ci		fe80::217:c8ff:fe28:65a6		
TASKalfa 6052ci		10.0.0.60		
TASKalfa 5052ci		10.0.0.113		
TASKalfa 6052ci		10.0.0.11		
TASKalfa 3050ci		100051		
devices] Use host name as p alect the features v	ort name ou want to use with this device.	10.00.51	SNMP	Settings C
devices] Use host name as p elect the features y Name	ort name ou want to use with this device. Description	10.00.51	SNMF	Settings C
devices] Use host name as p elect the features y Name V] KX DRIVER	ort name ou want to use with this device. Description (Recommended) Extended-functionalit	y printing	🏠 SNMF	Settings C
devices Use host name as p elect the features y Name Name FONTS FONTS	ort name ou want to use with this device. Description Recommended Extended-functionalit (Installed) Screen fonts that match the	y printing	🏠 SNMF	Settings C
devices Use host name as p elect the features y Name XX DRIVER FONTS Status Monitor 5	ort name ou want to use with this device. Description (Recommended) Extended-functionalit (Installed) Screen fonts that match the Advanced service for monitoring currer	y printing printer's fonts it printer status	Shime	v Settings C

3. Select No and click OK.



4. Unselect Set Duplex as default and then click Finish

Kyocera Product Library		×
Finished		
Your software is ready to use.		
Product VX DRIVER Uninstaller	Details InstalledKyocera TASKalfa 5052ci KX Installed	
	Fi	nish

5. In Device and Printers, right click on the newly created driver and select Printer Properties.

-12 Demois and Th	neis							u ^
÷- → - ↑	奇 > Control Pane	el > Hardware and Sou	nd > Devices and Printe	rs		~ O		م ر
Add a device	Add a printer	See what's printing	Print server properties	Remove device				≈ • 0
 Devices (4) 			-					
CBEPCO4	Cruzer Blade	Generic PnP Monitor	USB Optical Mouse					
Brother Maintenance USI	Brother	Fax	HP Designlet T830 36in	HP Printer	Kyocera Cloud Print and Scan	Kyocera TASKA S052ci KX	See what's printing Set as default printer Printing conferences	10 Microsoft XPS Document Writer
Printer		1					Printer properties Create shortcut	
OneNote (Desktop)	OneNote for Windows 10						Troubleshoot Properties	
w ky	ocera TASKalfa 5	052ci KX Manufacturer	: Kyocera	Status: 0 docum	sent(s) in queue			
1		Model Category	Kyocera Product Librar Laser printer	y				

6. Select the Advanced tab then click Printing Defaults...

🖶 Kyocera TASKalfa 5052ci KX Properties	×
General Sharing Ports Advanced Color Management Security Device Settings	
Always available	
O Available from 12:00 AM ↓ To 12:00 AM ↓	
Priority: 1	
Driver: Kyocera TASKalfa 5052ci KX V New Driver	
 Spool print documents so program finishes printing faster Start printing after last page is spooled Start printing immediately Print directly to the printer 	
Hold mismatched documents	
Print spooled documents first	
Keep printed documents	
Enable advanced printing features	
Printing Defaults Print Processor Separator Page	
OK Cancel Apply	

7. Select Mono, change the print size to A4 and then click Page Sizes...

🖶 Kyocera TASKalfa	5052ci KX Printing Defaults				?	×
Quick Print	Print size:		Collate: On			
🔳 Basic	Page Sizes	•		123		
H Layout	List enhancement Source:		0	۲		_
Einishing	Auto source selection	\sim	Orientation: F	Portrait		
ų. Thisining	Media type:		AL		◄	
Imaging	Unspecified	~	۲	0 0 0	С	
~	Printer default	\sim				-
Publishing			Duplex: Off			
다. Job			12, 1	2 3 2 3		
	Copies:		•	0 0		
← Advanced			Color: Black			-
			(
	Settings		2	5 🕘		
			0	0 🔍 🗆	EcoPrint	
	Batch copies					
E		ltem	De	tail		^
		Quick Print	Da	uturait		
		Color	Bla	nck		
		Collate	Or	1		
8		Duplex	Of	f		
		Pages per she	et Of	f		
		Basic				
		Source	Au	to source selection		
	PCL XL	Copies Carbon copies	1	f		~
Print proviou		Save Ac	, UI	Profiles	1	*
		Save As		FTOILES		
K YOCERa				ОК	Canc	el
					-	

8. Select A4 and then click OK

Page Sizes	?	\times
Select page size: 21	0 x 297 n	nm
A1 A2 SRA3 A3		
A4 A5 A6		~
New	Dele	te
	mm	
Name:		
	Sar	ve
ОК	Can	cel

9. The print size should now say A4 [100%], when it does click OK.

🖶 Kyocera TASKalfa 5052ci KX Printing De	efaults	?	×
Quick Print Print size:	Colla	te: On	
Basic Page Sizes			
Layout Source:		•	
Auto source selection	- Orier	ntation: Portrait	
Unspecified Destination:			
Printer default	∽ Dupl	ex: Off	
다. Job	[
Advanced			
Carbon copies Settings Batch copies Settings			
	Itam	Datail	•
	Guick Print Orientation Color Collate Duplex Pages per sheet Basic Source Copies	Portrait Black On Off Off Auto source selection	
PCL	XL Carbon copies	Off	~
Print preview	Save As	Profiles	
K YOCERa		OK Can	cel

10. In Printer Properties click General, change the printer name to Main Office Photocopier and then confirm that the setting you put into Printer Defaults are the same as what's shown in Preferences...

Kyocera TASKalfa 5052ci KX Prop	erties	Х
General Sharing Ports Advanced	Color Management Security Device Settings	
Main Office Photoco	pier	
Location:		
Comment:		
Model: Kyocera TASKalfa 50 Features	52ci KX	
Double-sided: Yes Staple: Yes Speed: 50 ppm Maximum resolution: 1200 dpi	Letter Legal Ledger (11 x 17) Statement Executive	
Prefe	rences Print Test Page	
	OK Cancel Appl	y